



LIQUID LEAK DETECTION SYSTEMS

OIL & GAS DIVISION

# FG-NET-LL

Long Line Digital Unit for Hydrocarbon Leak Detection Sense Cables

## Product Datasheet



- ▶ Digital, Fully Addressable
- ▶ Monitoring Up to 2400 meter FG-OD Sense Cables
- ▶ Touch Screen Interface
- ▶ Dynamic Leak Evolution Analysis
- ▶ TCP/IP & MODBUS/JBUS Connection
- ▶ Exclusive for FG-OD Range of Sense Cables

## Description

The FG-NET-LL Digital Unit is designed to be used with TTK FG-OD range of Digital Sense Cables, for industry Long Line application. In the event of a fault on the sense cables (leak or cable break):

### Primary responses from the FG-NET-LL:

- An audible alarm is triggered and a relay is activated.
- The touch screen of the panel displays the location of the leak (to the concerned sense cable) and details of the fault (the type of fault leak or cable break), including the time and date the fault is registered.
- Optional – integrated maps of the leak detection installation highlighting the location of the fault, available on the touch screen display of FG-NET-LL.

### Secondary advanced responses :

- Report to the DCS / SCADA / Safeguarding System via a JBUS/MODBUS protocol. The FG-NET-LL can drive dynamic drawings on the host DCS / SCADA/Safeguarding System.
- Send email alerts and SNMP traps to a LAN-connected DCS / SCADA / Safeguarding System, via a standard Ethernet connection.

## Features & Benefits

### FEATURES

- 7" (175mm) touch-screen gives a clear and detailed indication of the system status.
- User-friendly system - users can customise the system with the sub menus accessible from the home screen, to set up the panel.
- Up to 120 lengths of sense cables can be managed independently.
- The system's reaction time to faults is adjustable cable by cable.
- Temporal isolation (72 hours maximum) a or several sense cables.
- Up to 5000 events stored in the history log.
- Non-volatile memory (SD), for storing user settings and drawings.
- Three types of interface for communication with a BMS available.
  - TCP/IP connection via an Ethernet port.
  - JBUS/MODBUS RS232 or RS422/485 serial links.
  - 9 relay contacts: 8 configurable relays + 1 specific relay for power interruption.
    - Dual relay drive (e.g. 1 for BMS and 1 for solenoid valve);
    - Relay positions are defined by a LED indicator.
- Different security levels to provide maximum security.

### BENEFITS

- Dynamic Leak Evolution Analysis - The magnitude of a leak and its evolution in time can be analysed through the alarm logs. The number and sequence of addressable sections which report a leak, together with their timestamp, allow to monitor the leak's progression in time.
- Precise location of a leak and cable break to the concerned sense cable.
- Each sense cable is addressable and can be assigned a specific name.
- Multiple simultaneous leaks can be detected (120 cables = 120 potential alarms).
- When a cable break occurs, the system maintains its integrity by continuing to monitor all preceding cables for faults.
- Compatible with existing monitoring systems (Trend DCS etc.)
- Extension and upgrade of the system is easy.

## Touch Screen Menus

### Four menus available for configuration of the FG-NET-LL:

<b>Setup</b>	Main page for setting up the system architecture, cable isolation and reaction time rules, acknowledge mode, user access, relay status, time zone, language, sound alarm, serial links and network functionalities. An administrator level password is required to access this menu.
<b>Event log</b>	For viewing the recorded alarm history. A maximum of 5000 events can be stored in the event log.
<b>Cables</b>	To give the user a general overview of the site installation. The interactive floor plan can be viewed under this menu as an optional feature.
<b>Help</b>	Provides troubleshooting procedures, contact details of the manufacturer and the reference number of the unit.

# Screen Shots



Simultaneous alarms displayed on one screen



Dynamic map shows leak in real time



Easy setup of relays for each cable



User-friendly interface of configuration

## Technical Data

<b>Compatibility</b>	Digital sense cable and point sensor: FG-OD, FG-ODC, FG-ODR, FG-ODP Satellite devices: FG-BBOX, FG-BBOX-LL, FG-RELAYS Diversion box: FG-DEX Accessories: "TTK 8771" jumper cable, FG-CLOD, FG-TMOD, FG-NOD (x)
<b>Dimensions &amp; Weights</b>	Wall mounted W: 228 mm H: 303 mm D: 67 mm Weight: 2.3kg Rack mounted W: 483 mm H: 177 mm D: 74 mm Weight: 3kg
<b>Maximum Length of Sense Cable</b>	2400 meters (3 circuits x 40 cables x 20 m) (connected with 1000m jumper cable and Zener barrier MTL7760ac or equivalent)
<b>Accuracy</b>	Concerned sense cable
<b>Operating Languages</b>	English, French, German
<b>Voltage Input</b>	100 to 240 VAC, 50-60 Hz
<b>Power Consumption</b>	36VA Max
<b>Working Temperature Range</b>	5°C to 40°C
<b>Working Humidity Range</b>	5% to 80% non-condensing
<b>Relay Types</b>	Volt free dry contact (NO, NC, COM)
<b>Relay Numbers</b>	9 (8 + 1 power failure relay)
<b>Serial Connection</b>	MODBUS/JBUS RS232 or RS422/485
<b>Maximum Switching Voltage</b>	125 V AC and 220 V DC
<b>Maximum Switching Capacity</b>	60 W (30V x 2A)
<b>Ingress Protection</b>	IP40 - Indoor use only

## Identification Codes

<b>FG-NET-LL (Wall mounted / Rack mounted)</b>	Long line digital unit for hydrocarbon leak detection sense cables in wall mounted in plastic enclosure / in rack mounted in 19" & 4U
<b>FG-BBOX</b>	Digital black box 100-240V
<b>FG-RELAYS</b>	Digital 24 external relays box 100-240VAC 1.3A 50/60Hz
<b>FG-OD/ODC/ODR, 7, 12, 20</b>	Digital sense cables in lengths of 3m, 7m, 12m, 20m
<b>FG-ODLxxyy/xyy/xyy</b>	Customerized Hydrocarbon sense cable, with connectors at each end xx= section length (3, 7, 12 or 20); yy= section numbers i.e.: FG-ODL2004: the mounting of 4 section cables FG-ODL : 4 sections of 20m
<b>Accessories:</b>	
<b>FG-DEX</b>	ATEX bus diversion box for FG-OD hydrocarbon sense cable
<b>FG-NOD (x)</b>	"OD bus 8771" jumper cable x meters with connectors

## Certificates



FG-NET-LL digital unit meets the TÜV requirements.  
FG-NET-LL leak detection and locating system is UL Listed.  
FG-OD sense cables which are certified by ATEX can be connected to the FG-NET-LL digital unit.

All the connections in the FG-NET-LL digital unit must be done with the power supply switched off.  
Read carefully the installation procedure for the FG-NET digital unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this product. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.  
FG-NET, FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2020

- **TTK Headquarters** / 19 rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / [www.ttk.fr](http://www.ttk.fr) / [ventes@ttk.fr](mailto:ventes@ttk.fr)
- **TTK Oil & Gas Division** / 19 rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / [www.ttk.fr](http://www.ttk.fr) / [rrisi@ttk.fr](mailto:rrisi@ttk.fr)
- **TTK UK Ltd.** / 3 Luke Street / London EC2A 4PX / United Kingdom / T : 0207 729 6002 / F : 0207 729 6003 / [www.ttkuk.com](http://www.ttkuk.com) / [sales@ttkuk.com](mailto:sales@ttkuk.com)
- **TTK Pte Ltd.** / #09-05, Shenton House, 3 Shenton Way / Singapore 068805 / Tel.+65-6220.2068 / Mob: +65.9271.6191 / Fax: +65-6220.2026 / [www.ttk.sg](http://www.ttk.sg) / [sales@ttk.sg](mailto:sales@ttk.sg)
- **TTK Asia Ltd.** / 2107-2108 Kai Tak Commercial Building / 317 Des Voeux Road Central / Hongkong / Tel.+852.2858.7128 / Fax.+852.2858.8428 / [www.ttkasia.com](http://www.ttkasia.com) / [info@ttkasia.com](mailto:info@ttkasia.com)
- **TTK Middle East FZCO** / Building 6EA, Office 510 PO Box 54925 / Dubai Airport Free Zone / UAE / T: +971 4 70 17 553 / M: +971 50 259 66 29 / [www.ttkuk.com](http://www.ttkuk.com) / [cgalmiche@ttk.fr](mailto:cgalmiche@ttk.fr)
- **TTK Deutschland GmbH** / Berner Strasse 34 / 60437 Frankfurt / Deutschland / T : +49(0)69-95005630 / F : +49(0)69-95005640 / [www.ttk-gmbh.de](http://www.ttk-gmbh.de) / [vertrieb@ttk-gmbh.de](mailto:vertrieb@ttk-gmbh.de)
- **TTK North America Inc** / 1730 St. Laurent Boulevard, Suite 800 / Ottawa, ON K1G 5L1 / Canada / T : +1 613 566 5968 / [www.ttkcanada.com](http://www.ttkcanada.com) / [info@ttkcanada.com](mailto:info@ttkcanada.com)
- **Thomas Sales & Marketing Inc. TTK Master Distributor For USA** / 7200 W 66th St / Bedford Park, IL 60638 / The United States / T: +1 630-518-4724 / [www.ttkusa.com](http://www.ttkusa.com) / [dmolk@ttkusa.com](mailto:dmolk@ttkusa.com)